

This Page Is Inserted by IFW Operations  
and is not a part of the Official Record

## **BEST AVAILABLE IMAGES**

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images may include (but are not limited to):

- BLACK BORDERS
- TEXT CUT OFF AT TOP, BOTTOM OR SIDES
- FADED TEXT
- ILLEGIBLE TEXT
- SKEWED/SLANTED IMAGES
- COLORED PHOTOS
- BLACK OR VERY BLACK AND WHITE DARK PHOTOS
- GRAY SCALE DOCUMENTS

IMAGES ARE BEST AVAILABLE COPY.

**As rescanning documents *will not* correct images,  
please do not report the images to the  
Image Problems Mailbox.**

(19)



Europäisches Patentamt  
European Patent Office  
Office européen des brevets



(11)

EP 1 079 655 A1

(12)

## EUROPEAN PATENT APPLICATION

(43) Date of publication:

28.02.2001 Bulletin 2001/09

(51) Int Cl.7: H04Q 7/38

(21) Application number: 99306649.7

(22) Date of filing: 23.08.1999

(84) Designated Contracting States:

AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU  
MC NL PT SE

Designated Extension States:

AL LT LV MK RO SI

(71) Applicant: LUCENT TECHNOLOGIES INC.  
Murray Hill, New Jersey 07974-0636 (US)

(72) Inventors:

• Palat, Sudeep Kumar  
Swindon, Wiltshire SN5 6EE (GB)

• Roberts, Michael  
Southend on Sea, Essex (GB)  
• Yamini, Hatel  
London NW11 8NL (GB)


(74) Representative: Williams, David John et al  
Lucent Technologies UK Limited,  
5 Mornington Road  
Woodford Green, Essex IG8 0TU (GB)

(54) RAU optimisation for UMTS URA connected state

(57) There is disclosed a technique for the optimisation of routing area updates during inter-system

handover between GSM/GPRS and UMTS in a URA connected state in UMTS.

FIG. 5



EP 1 079 655 A1

## Description

### Field of the Invention

[0001] The present invention relates to routing area updates (RAUs) that take place as a mobile terminal moves from one radio access coverage area to another, and particularly to such movement when the mobile terminal is in a so-called standby mode in which no data is being transmitted or received.

### Background to the Invention

[0002] GSM (Global System for Mobile Communications) radio coverage, which may also be referred to as second generation (2G) radio coverage, is quite extensive today. During the introduction of UMTS (Universal System for Mobile Telecommunications), which may also be referred to as third generation (3G) radio coverage, UMTS radio coverage is expected to be limited to urban areas.

[0003] Thus UMTS radio coverage will cover only parts of the more extensive GSM radio coverage areas. Even within UMTS coverage areas, the UMTS radio coverage cannot be expected to be contiguous. For example, given that the frequency used for UMTS is higher than that for GSM, the in-building penetration will not be as good as GSM. This will result in small pockets (such as inside buildings) without UMTS coverage within the overall UMTS coverage area. Thus, only GSM radio coverage will be available in these pockets.

[0004] A dual mode GSM and UMTS mobile terminal (a mobile terminal is referred to as user equipment (UE) in UMTS) can communicate using either one of the two radio access systems. If a dual mode mobile terminal communicating via the UMTS radio link goes out of UMTS coverage, to an area with only GSM coverage, it can expect to continue the communication via the GSM radio link, but with a consequential degradation of service. Similarly a dual mode mobile terminal in an area with only GSM radio coverage which moves into an area with UMTS coverage can expect to switch to the UMTS radio link to improve service.

[0005] Thus as a dual mode mobile terminal moves around within radio access areas, changes in the type of radio access can be expected as the available radio access systems change. As the mobile terminal moves between radio access areas routing area updates occur to notify the necessary support network of the new position of the mobile in the routing area associated with the particular radio access type. Changing between two radio access systems involves additional signalling and can also lead to outages during the transition between the two systems. The impact of the additional signalling and outages depends on the network architecture and the protocols chosen.

[0006] Packet data communication can be bursty, and there can consequentially be long periods when a mo-

bile terminal is not sending or receiving data. When a mobile terminal is in packet communication mode in the GSM network, it is communicating via the GPRS interface. A certain time-out period after sending the last packet, the mobile terminal will transfer to a standby state. In the UMTS network, after a certain time out period of no activity, the terminal will first transfer to a so-called 'UTRAN Registration Area (URA) connected' state. In the URA connected state, the connection between the mobile terminal and the UTRAN is maintained on the lu link. After a longer period of time, the context in the UTRAN which identified the link to the mobile can be removed and the lu connection torn down. While the state of the mobile terminal after the lu connection has been torn down has not been given any specific name in the UMTS standards, it shall be referred to herein as a UMTS standby state.

[0007] In the proposed implementations of both the GSM and UMTS standby states, a mobile terminal always performs a routing area update as it moves between radio access system coverage areas at all times, even when it is in the standby state.

[0008] It is an object of the present invention to provide an improved technique for reducing unnecessary routing area updates, which still ensures the location of a mobile terminal is known when the mobile terminal starts data communication after being in a standby state.

### Summary of the Invention

[0009] According to the present invention there is provided in a packet radio access network architecture having a common routing area controlled by a core network and supported by a first wireless access system and a second wireless access system a method of controlling routing area updates, wherein in at least the first radio access system there is provided a mode of operation in which a radio link is maintained between a mobile terminal and the first radio access system after completion of a data transmission, a routing area update only taking place if the mobile is located in the second radio access system routing area when the next data transmission is initiated, wherein if packet transmission is initiated by the network the first radio access system receives a paging request, and responsive to receipt of the paging request the first radio access system pages the core network common routing area.

[0010] The first radio access system may page the core network common routing area by sending a paging request to the core network.

[0011] Responsive to the paging request, the core network may send a paging request to the second radio access system.

[0012] The first radio access system may be a UMTS system and the second radio access system may be a GSM system. The UMTS system may generate a RNTI paging signal to the common routing area, and the core

network may generate a P-TMSI paging signal to the core network routing area.

[0013] The core network may generate a modified paging signal to the second routing area based on the RNTI paging signal.

[0014] The mobile terminal may respond to the paging signal with a routing area update.

[0015] If packet transmission is initiated by the mobile, the packet transmission initiation may include a routing area update.

[0016] Thus a mobile terminal (or user equipment) moving back and forth between a 2G environment and a 3G environment without sending any data will not generate any signalling. This frequent switching between 2G and 3G environments is likely to happen at the edges of the patchy 3G coverage areas.

[0017] This allows almost all of the 2G and 3G implementation of the serving GPRS support nodes (SGSNs) to be kept separate. The routing area update (RAU) performed before sending any data from the new access network will result in the context transfer from the 2G to the 3G and also the set up of the proper state machines and protocol stack.

[0018] The invention will now be described by way of example with reference to the accompanying drawings, in which:

#### **Brief Description of the Drawings**

[0019]

Figure 1 illustrates the patchy nature of UMTS radio coverage in a GSM coverage area;

Figure 2 illustrates the conventional network architecture of UMTS and GSM having distinct routing areas, with respective distinct serving GPRS support nodes;

Figure 3 illustrates a network architecture in which the UMTS and GSM routing areas are common, with a shared GPRS support node; and

Figure 4 illustrates a network architecture in which UMTS and GSM routing areas are common, with a partially shared GPRS support node; and

Figure 5 illustrates a further adaptation of the network architecture of Figure 2 in an improvement to the routing area update technique in the particular example of a 'URA connected' state in a UMTS mobile terminal.

#### **Description of Preferred Embodiment**

[0020] Figure 1 illustrates the coverage expected to be provided by UMTS in a GSM area. The shaded areas represent areas with only GSM (2G) coverage. The non-shaded areas represent areas with both GSM (2G) and UMTS (3G) coverage.

[0021] Thus the whole of the area 2 is provided with GSM coverage. The smaller area 4 within the area 2 is

intended to be provided with UMTS coverage in addition to GSM coverage. However pockets, designated by reference numeral 6, exist within the UMTS coverage area 4, such that only GSM coverage is provided in the pockets 6.

[0022] The general current conventional network architecture for supporting the radio coverage as illustrated in Figure 1 is as shown in Figure 2. The GSM radio access area and the UMTS radio access area are considered as independent systems having distinct routing areas, each served by a different serving GPRS support node (SGSN). Each SGSN is thus associated with distinct routing areas.

[0023] The SGSNs provide the support node for the respective radio systems to support packet switched communications.

[0024] Referring to Figure 2, the GSM radio access area supports a first routing area 200 designated RA1, and the UMTS radio access area supports a second routing area 202 designated RA2. It can be seen that the second routing area RA2 is over-layed on the first routing area RA1.

[0025] The first routing area RA1 is associated with a GSM/GPRS BSS 204 and a SGSN 208, which may be labelled as a 2G SGSN since it is provided to support the 2G GSM/GPRS network. The second routing area RA2 is associated with a UMTS terrestrial radio access network (UTRAN) 206 and a SGSN 210, which may be labelled as a 3G SGSN since it is provided to support the 3G UMTS network. A common 2G/3G gateway GPRS support node (GGSN) 212 is provided to support both the 2G GSM/GPRS network and the 3G UMTS network.

[0026] A connection 214 connects the GSM/GPRS BSS 204 to the base stations supporting the GSM/GPRS cells in the routing area RA1. The GSM/GPRS BSS 204 is connected to the 2G SGSN 208 via a Gb interface connection 218, and the 2G SGSN 208 is connected via a connection 222 to the 2G/3G GGSN 212. The UTRAN 206 is connected to the UMTS core network via a connection 216. The connection 216 connects the UTRAN 206 to the base stations supporting the UMTS cells in the routing area RA2. The UTRAN 206 is connected to the 3G SGSN 210 via an Iu interface connection 220, and the 3G SGSN 210 is connected to the 2G/3G GGSN 212 via a connection 224. The 2G SGSN 208 and the 3G SGSN 210 are interconnected via a Gn interface connection 209.

[0027] If a mobile terminal is compatible with both GSM/GPRS and UMTS, then when it is in a radio access area covered by both systems it may connect to either network. For packet transmissions, where GSM/GPRS and UMTS are supported, a mobile terminal will preferably operate in UMTS mode to take advantage of the better transmission supported thereby.

[0028] In the conventional network architecture of Figure 2, every time a mobile moves between 2G and 3G coverage, a routing area update (RAU) is required irre-

spective of the state of the mobile terminal, i.e. whether it is in standby mode or otherwise. These RAUs inform the respective SGSN of the location of the mobile terminal (i.e. whether in routing area RA1 or RA2) and also set up the part of the protocol stack at the SGSN required for the data transmission.

**[0029]** The RAUs performed when the mobile terminal moves between 2G and 3G are inter-SGSN RAUs and hence the home location register (HLR) also needs to be updated, since the HLR stores the correct SGSN number of a particular mobile terminal. Thus the HLR needs to be updated every time a mobile terminal 'moves' from one SGSN to another. The interconnection of the HLR in the network architecture of Figure 2 is not shown for reasons of clarity, since it is not relevant to the present invention and will be understood by one skilled in the art.

**[0030]** A PDP context is a context initiated by a mobile terminal for communication. If the user has a PDP context active, the GGSN and GPRS tunnelling protocol (GTP) links must be set up. The GTP between the GGSN and the SGSN needs to be updated when a mobile terminal moves from one SGSN to another with a PDP context active. Both of these involve considerable signalling overheads.

**[0031]** It is therefore apparent that these routing area updates which take place as a mobile terminal moves between routing areas whilst in a standby mode waste valuable resources. Avoidance of the RAU update will not only reduce signalling traffic but also improve Quality of Service (QoS).

**[0032]** A network architecture for avoiding the RAU whenever a mobile terminal in standby state moves between 2G and 3G is shown in Figure 3. Like reference numerals are used in Figure 3 to identify elements corresponding to elements shown in Figure 2.

**[0033]** The network architecture of Figure 3 differs from that of Figure 2 in that the 2G SGSN 208 and the 3G SGSN 210 have been replaced by a single 2G/3G SGSN 300 which connects to the GSM/GPRS BSS 204 via the Gb interface connection 218 and connects to the UTRAN 218 via the Iu interface connection 220. The 2G/3G SGSN 300 connects to the 2G/3G GGSN 212 via connection 302.

**[0034]** As a result of the shared 2G/3G SGSN 300, the routing areas RA1 and RA2 of Figure 2 become a shared routing area, designated as RA3 in Figure 3. Thus the GSM/GPRS BSS 204 supports a radio access area designated by reference numeral 304 corresponding to routing area RA3. Similarly, the UTRAN 218 supports a radio access area 306 corresponding to the same routing area RA3.

**[0035]** In the network architecture of Figure 3, the 2G and 3G radio access systems are served by the same SGSN, and consequently are associated with the same routing area. This avoids the requirement to perform a routing area update when crossing between 2G and 3G coverage areas. However, with such an architecture, the

SGSN becomes quite complex. This is because a mobile terminal in the standby state moving between 2G and 3G will not generate a radio access update. In other words, the SGSN cannot be aware of the position of the mobile terminal, and the mobile terminal can be located either in the 2G or in the 3G part of the routing area. Thus when a packet from the network arrives at the SGSN for transmission to a mobile terminal, the SGSN must page the mobile in both the 2G and 3G radio access systems to determine the location of the mobile terminal. In paging a mobile, the SGSN broadcasts a paging signal, which identifies the mobile, in the routing area. The paging signal indicates to the mobile identified therein that the core network has a packet for transmission to the mobile. When a mobile receives a paging signal which identifies that mobile, if the mobile is ready to receive the packet by sending a paging response to the network.

**[0036]** The protocol stack and the mobility management state machine for the 2G and 3G networks at the SGSN are different. Depending on where the mobile terminal's paging response came from, either the 2G or 3G area, the mobility management state machine must adapt to the appropriate behaviour. The appropriate protocol stacks must be set up before the data is sent to the terminal. All this must be done autonomously within the SGSN based on the paging response. This complicates the state machines for mobility management.

**[0037]** If the mobile terminal has data to send, the situation is even more complex. The SGSN must be prepared to accept data from either 2G or 3G at any time in the standby state. This is complex because the appropriate protocol stacks are not set up prior to the mobile terminal sending the data and there are no signalling messages exchanged at all before the data packet is sent.

**[0038]** A further modification to the network architecture of Figure 3 in accordance with the present invention is shown in Figure 4. Again like reference numerals are used to designate elements in Figure 4 corresponding to elements shown in Figures 2 or 3.

**[0039]** The network architecture of Figure 4 is similar to that shown in Figure 3, except that the 2G/3G SGSN 300 has been replaced by a partially split 2G/3G SGSN 400. The split 2G/3G SGSN 400 allows larger separation of the implementation of 2G and 3G elements than in the combined 2G/3G SGSN 300 of Figure 3. This allows the 2G and 3G parts of the SGSN to be largely separate thereby simplifying the SGSN development. As shown in Figure 4, the 2G/3G SGSN comprises a 2G functional part 406 and a 3G functional part 404.

**[0040]** In accordance with the present invention, the routing area is still a common routing area RA3 which spans both the 2G radio access area and the 3G radio access area.

**[0041]** A mobile terminal in a standby mode of operation moving between 2G and 3G radio access areas within the same routing area does not perform a routing

area update. Thus, referring to Figure 1, a mobile terminal in standby mode which moves from one of the pockets 6, into the 3G coverage area 4 and then into the 2G coverage area 2 does not perform any routing area updates.

**[0042]** When the mobile terminal in the standby state wants to send data, then one of two operations occur. If the mobile terminal is in the same radio access network as it was when it last sent any data, the procedure to be followed for sending the new data is exactly as defined in that radio access network by 2G or 3G. If the mobile terminal is in the other access network than the one from which it sent data last, a routing area update must be performed before sending the data. For example, a terminal in standby state in 2G will not perform a routing area update when it crosses into 3G, but will do so if it still remains in the 3G radio access area when it has any data to transmit.

**[0043]** While the mobile terminal is in the standby state in 2G or 3G, if the SGSN receives data which is to be sent to the mobile, it must page the entire routing area, which includes both 2G and 3G coverage. If the mobile terminal is in the same radio access network as it was when it last sent any data, the procedures to be followed is exactly as defined in 2G or 3G, and a normal paging response is generated. If the terminal has changed between 2G and 3G between the time it last sent or received any data and the paging message, it performs a routing area update instead of a paging response. The network then accepts this routing area update as a paging response.

**[0044]** Thus, a mobile terminal in the standby state moving back and forth between 2G and 3G environments without sending any data will not generate any signalling.

**[0045]** This frequent switching between 2G and 3G environments is likely to happen at the edges of the patchy 3G coverage.

**[0046]** Thus, a routing area update is performed only if it is necessary at the time that the data used to be transmitted or received.

**[0047]** This allows almost all of the 2G and 3G implementation of the SGSN to be kept separate. The RAU performed before sending any data from the other access network will result in the context transfer for the mobile terminal from the 2G to the 3G functional part 404, and also the set up of the proper state machines and protocol stack.

**[0048]** The paging message will still have to be sent via both access networks, but the other SGSN only needs to pass the paging message transparently without processing it or maintaining any state machine.

**[0049]** It should be possible for the SGSN to identify from the RAI and P-TMSI, whether the user was last registered in the 2G or 3G network. Normally, the RAI provides this distinction. If, as in this case, the same RAI is used for both 3G and 2G, then the P-TMSI address space for 2G and 3G should be disjoint.

**[0050]** This is an operator configuration issue.

**[0051]** If the mobile terminal happens to be in "other" coverage area while the Periodic Routing Area update timer ran out, it should perform a regular periodic routing area update and will then be considered as registered in that access network.

**[0052]** In the above, a technique has been discussed for improving efficiency when the mobile terminal is in the standby state. As indicated above, for a mobile terminal in the GSM/GPRS mode of operation, the mobile terminal is either in an active communication state or in the standby state. For a mobile terminal in a UMTS mode of operation, the mobile terminal additionally has a 'pre-standby' mode of operation called the URA connected state.

**[0053]** During this URA connected state, although no packet transmission takes place UTRAN registration area updates still take place as the mobile terminal moves around in the URA. It would therefore also be advantageous to apply the principles discussed hereinabove in the URA connected state, such that routing area updates are not carried out if there is no data being transmitted. Although the technique described hereinabove partially works in URA connected state, there is a drawback which prevents its general application, as discussed hereinbelow.

**[0054]** In the URA connected state a radio network controller (RNC) in the UTRAN maintains the link with the mobile terminal in the routing area, and the 3G SGSN maintains a link with the UTRAN 206 via the Iu interface connection 220. If the principles are applied as described above, then as the mobile terminal moves between different radio access areas it performs no routing area updates if it is in the URA connected state. When the mobile terminal has data to transmit it performs a routing area update if it is now connected in a different radio access network. Thus, when the mobile terminal transmits data, the principle of the above-described technique for the standby mode of operation works additionally in the URA connected state.

**[0055]** If the principle of the standby mode are applied and the mobile terminal performs no routing area updates in the URA connected state, and the network initiates a data transmission, then a problem may arise. In the URA connected state, as discussed hereinabove, the network still assumes the mobile to be attached to the UMTS radio access system owing to the link maintained between the UTRAN and the routing area. Thus when the network wishes to transmit data the network pages the URA only from the UTRAN. If the mobile has not moved from the 3G routing area since its last packet transmission, then operation continues as normal. If the mobile has moved, however, then the paging by the UTRAN will be unsuccessful, as no paging is carried out by the GSM/GPRS radio access system. Thus the above-described technique for reducing routing area updates in the standby state cannot be safely implemented in the URA connected mode of operations.

**[0056]** Therefore in the following there is presented a modified technique for a more efficient implementation of routing area updates for when a mobile terminal supporting UMTS operation is in the URA connected state. This technique is not limited to the network architecture of Figure 3 or 4. Although it may be applied in such architectures, it is equally effective in an architecture such as that of Figure 2 where the SGSNs for the respective radio access systems are entirely distinct.

**[0057]** Referring to Figure 5, there is shown a network architecture corresponding to that of Figure 2 for the purpose of illustrating the technique for use in the URA connected mode of operation. Like reference numerals are used to denote like elements.

**[0058]** Referring to Figure 5, the routing area RA2 is conventionally sectioned into a plurality of UTRAN registration areas 500. In the URA connected state the UTRAN maintains a context for the mobile terminal which holds, specifically the UTRAN registration areas in which the mobile terminal was last in when it last made a packet transmission. The UTRAN is connected via the lu interface to the 3G SGSN 210.

**[0059]** In a conventional system, in the URA connected state when the network wishes to send data to the mobile terminal, the radio network controller (RNC) in the UTRAN pages the whole of the routing area RA2 because of the connection maintained from the 3G SGSN to the UTRAN. The routing area RA1 is not paged. If the mobile terminal moves into the routing area RA1 in the URA connected state, then a routing area update takes place.

**[0060]** In accordance with the new technique, when the mobile terminal is in the URA connected state, no routing area updates take place as the mobile terminal moves around between radio access.

**[0061]** If the mobile terminal wishes to send data, then as in the operation described hereinabove for the standby state the mobile performs a routing area update if the mobile terminal has moved to a new radio access area since its last communication.

**[0062]** If the network wishes to send data to the mobile terminal, then as conventionally an indication of such is provided to the UTRAN which still has an association for the mobile terminal (referred to as a UE in UMTS) via the lu interface to the SGSN. Responsive thereto, the UTRAN issues two paging signals, as discussed hereinafter

**[0063]** The first paging signal is the conventional radio network temporary identifier (RNTI) paging signal issued to the URA routing area RA2 supported by the UMTS radio access network. The second paging signal is a paging signal to initiate a paging of the routing area RA1. The second paging signal may take several forms. The second paging signal requires a new 'paging request' message across the lu interface to the 3G SGSN.

**[0064]** In a first embodiment, the routing area is paged using the standard packet temporary mobile subscriber identifier (P-TMSI) paging signal. This does not require

any new messages to be defined over the Gb interface or the air interface. The UTRAN generates the second paging signal by sending a paging request over the associated lu connection on line 220 to the 3G SGSN 210.

The 3G SGSN 210 creates a paging message with P-TMSI identifier responsive to the paging request on interface 220, and sends it on the Gn interface on line 209 to the 2G SGSN 208. Alternatively for a combined 2G/3G SGSN the P-TMSI identifier is transferred internally.

Responsive to the P-TMSI paging signal, the 2G SGSN 208 communicates with the GSM/GPRS BSS 204, which sends the P-TMSI paging signal to the routing area RA1.

In a second embodiment, the 2G routing area ? and the 3G routing area are paged using an RNTI identifier. This requires a new message to be defined over the Gb interface and the air interface between the GSM/GPRS BSS and the 2G network. The UTRAN generates a new type of paging message, which is sent via the 3G SGSN and 2G SGSN to the GSM/GPRS BSS. The GSM/GPRS BSS then broadcasts the new paging message to the routing area RA1.

As described earlier, a routing area update by the mobile terminal is accepted as a paging response by the network.

Although the invention has been described with particular reference to an environment in which the radio access areas are GSM/GPRS and UMTS, it will be appreciated that the invention is more broadly applicable to environments in which at least two radio access areas overlap.

## Claims

1. In a packet radio access network architecture having a common routing area controlled by a core network and supported by a first wireless access system and a second wireless access system a method of controlling routing area updates, wherein in at least the first radio access system there is provided a mode of operation in which a radio link is maintained between a mobile terminal and the first radio access system after completion of a data transmission, a routing area update only taking place if the mobile is located in the second radio access system routing area when the next data transmission is initiated, wherein if packet transmission is initiated by the network the first radio access system receives a paging request, and responsive to receipt of the paging request the first radio access system pages the core network common routing area.
2. The method of claim 1, wherein the first radio access system pages the core network common routing area by sending a paging request to the core network.

3. The method of claim 3, wherein the responsive to the paging request, core network sends a paging request to the second radio access system.
4. The method of claim 1 or claim 2 in which the first radio access system is a UMTS system and the second radio access system is a GSM system. 5
5. The method of claim 3, wherein the UMTS system generates a RNTI paging signal to the common routing area, and the core network generates a P-TMSI paging signal to the core network routing area. 10
6. The method of claim 3, wherein the core network generates a modified paging signal to the second routing area based on the RNTI paging signal. 15
7. The method of claim 7 wherein a mobile terminal responds to the paging signal with a routing area update. 20
8. The method of any preceding claim wherein if packet transmission is initiated by the mobile, the packet transmission initiation includes a routing area update. 25

30

35

40

45

50

55







FIG. 3




FIG. 4





FIG. 5





European Patent  
Office

# EUROPEAN SEARCH REPORT

Application Number  
EP 99 30 6649

DOCUMENTS CONSIDERED TO BE RELEVANT		
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim
A	WO 98 32299 A (NOKIA TELECOMMUNICATIONS OY ; KARI HANNU (FI); RAHKONEN PEKKA (FI)) 23 July 1998 (1998-07-23) * page 8, line 16 - page 10, line 21 *	1-8
A	WO 98 32304 A (NOKIA TELECOMMUNICATIONS OY ; KANGAS ISMO (FI); MUSTAJAERVI JARI (F)) 23 July 1998 (1998-07-23) * page 6, line 25 - page 10, line 8 *	1-8
		CLASSIFICATION OF THE APPLICATION (Int.Cl.7)
		H04Q7/38
		TECHNICAL FIELDS SEARCHED (Int.Cl.7)
		H04Q
The present search report has been drawn up for all claims		
Place of search	Date of completion of the search	Examiner
THE HAGUE	18 January 2000	Weinmiller, J
<p>CATEGORY OF CITED DOCUMENTS</p> <p>X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document</p> <p>T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons a : member of the same patent family, corresponding document</p>		

EPO FORM 1503 (02.92) (P4/C01)

**ANNEX TO THE EUROPEAN SEARCH REPORT  
ON EUROPEAN PATENT APPLICATION NO.**

EP 99 30 6649

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report.  
The members are as contained in the European Patent Office EDP file on  
The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

18-01-2000

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
WO 9832299 A	23-07-1998	FI 970236 A	21-07-1998
		AU 5665298 A	07-08-1998
		EP 0953263 A	03-11-1999
		ZA 9800407 A	03-08-1998
WO 9832304 A	23-07-1998	FI 970238 A	21-07-1998
		AU 5665998 A	07-08-1998
		EP 0953270 A	03-11-1999
		ZA 9800408 A	29-07-1998

EPO FORM P459

For more details about this annex : see Official Journal of the European Patent Office, No. 12/82